

# kerlink

communication is everything

## Wirnet™ iBTS LoRaWAN® Outdoor Gateway for the Internet of Things



Standard Version



Compact Version

The “Wirnet™ iBTS” is the ideal gateway to support your smart city, smart building or every smart project as it combines both an excellent Outdoor coverage (more than 15km in direct line-of-sight and 2km in urban environment) and operational excellence.



Smart Cities



Smart Building



Smart Metering



Smart Agriculture & Environment

Kerlink is certified ISO9001: 2015 by AFNOR certification. The Quality Management System gives high priority to Customer satisfaction and progress implementation.



### Key Features

- **Outdoor LoRa® Gateway,**
- Supported unlicensed bands : 863-874.4MHz (EMEA, India), 902-928MHz (North America), 915-928MHz (APAC, Latin America),
- Supported LoRaWAN® regional parameters: EU863-870, IN865-867, RU864-870, US902-928, AU915-928, AS923, KR920-923,
- **Modular configurations:**
  - from 16 channels (1 x LoRa RF modem) to 80 channels (4 x LoRa RF modem),
  - Single omnidirectional antenna, spatial diversity, dual polarization, tri-sectorization,
  - Possibility to support multiple unlicensed bands in a single gateway,
- Backhaul connectivity: Cellular 2G/3G/4G evolutive to 5G (mini-PCIe module), Ethernet 10/100 Mbps (RJ45),
- **Geolocation ready:** Using the fine timestamps on ALL the channels for improved geolocation services thanks to FPGA. Fully compliant with Semtech reference design v2. No proprietary locked solution; **Synchronization with GPS, combines RSSI and TDOA measurements.**

### Key Differentiators

#### High performance, reliability & future-proof

- Semtech Reference Design v2,
- Built-in high rejection filters,
- LoRa-E™ Ready: Evolutive design using modem SDR (Software Design Radio) architecture.

#### Secure HW and SW architecture

- SecureBoot (Signed firmware),
- SecureStorage (keys and certificates in secured area) using ProvenCore™ solution,
- Secured links and backhaul protection (OpenVPN/IPsec),
- Reboot (watchdog) and recovery to previous Management config (or factory config if the boot issue is not fixed).

All product specifications are subject to change without notice (V2.7)

**kerlink**  
communication is everything

**Wirnet™ iBTS**  
LoRaWAN® Outdoor Gateway for the Internet of Things

## Zoom on “iBTS Standard” Version

- **Modular configuration:**
  - 1 x UC module,
  - **Select up to 2 x WAN modules (optional),**
  - **Select up to 4 x LoRa® RF modem modules (16 channels each),** Each LoRa RF modem allows 16ch RX (125 kHz, multi Spreading Factor) + 2ch RX (250kHz or 500kHz, mono Spreading Factor) + 2ch FSK + 2ch TX (without antenna diversity) to get up to 80 ch RX (with 4 x LoRa RF modem),
  - Size: 295 x 317 x 125 mm (including mounting kit),
  - Ingress protection (IP66),
  - Weight:
    - About 6,2Kg (including mounting kit) with 1 x LoRa RF modem,
    - About 7,2Kg (including mounting kit) with 3 x LoRa RF modems.

## Zoom on “iBTS Compact” Version

- **Compact configuration:**
  - 1 x UC module,
  - 1 x WAN module (**optional**),
  - 1 x LoRa® RF modem module (16 channels),
  - **Size:** 357 x 189 x 150 mm (including mounting kit),
  - Ingress protection (IP67),
  - **Weight:** about 3Kg (including mounting kit).

## Technical Features

- Sniffer for LBT (Listen Before Talk),
- Rx Sensitivity: -141 dBm (SF12),
- TX Conducted Power: configurable from 5dBm to 30dBm,
- Range -40°C +60°C, (for gateway only, without power supply),
- Humidity: 5% to 95%,
- Out-band radio scanners to monitor the entire band to detect real load of the band (Spectrum analysis compliant),
- Supercapacitors for clean shut down of applications in case of power failure,
- Power:
  - Power Over Ethernet **30W** for **Compact** version (accessory),
  - Power Over Ethernet **60W** for **Standard** version (accessory),
  - Power Over Ethernet 48V DC class 4 (accessory),
  - DC power supply (ex : solar panel use) : 11 to 56V DC (accessory),
  - Power control : ignition detection, software OFF switching, ON/OFF button.

## Software Features

- **Same FW as Wirnet™ iStation and iFemtoCell:** same user experience, quicker integration,
- **Dynamic web interface (On-the fly modifications),**
- **Programmable Gateway:** Toolchain, libraries and header files for compilation of in-house SW, or extra packages additions,
- **Including:**
  - Operating System: KerOS with embedded GNU/Linux based on Yocto 2.4 and LTS kernel 4.14,
  - Native Language Support: Python2, C/C++ and Shell,
  - Included packages: SQLite (Database), Connman/ Ofono, NTPd, lighttpd.

## Value-added Services

- **Free access to Kerlink Wiki for customers,**
- Plug & Play installation (option),
- Wirnet™ iBTS is part of the end-to-end LoRa® connectivity solution with Kerlink Wanesy™ Management Center, remote monitoring and Operations Management suite (option),
- Maintenance Services (option),
- **Kerlink Project Management:** a comprehensive service offering and a global network of specialist integrators to support your entire project.

Thanks to their expertise and experience, Kerlink teams are fully mobilized to help you develop your business and reduce your operational and commercial risks.

**Don't hesitate to contact us:**

**kerlink**  
communication is everything

sales@kerlink.fr  
+ 33 2 99 12 29 00  
1 rue Jacqueline Auriol  
35235 Thorigné-Fouillard  
France

All product specifications are subject to change without notice (V2.7)

kerlink  
communication is everything

Wirnet™ iBTS  
LoRaWAN® Outdoor Gateway for the Internet of Things



Wirnet™ iBTS (standard)



Wirnet™ iBTS Compact

All product specifications are subject to change without notice (V2.7)

**kerlink**  
communication is everything

**Wirnet™ iBTS**  
LoRaWAN® Outdoor Gateway for the Internet of Things

## Wirnet™ iBTS Compact - Ordering references

### Product Ordering References

| Reference    | Designation                                 | Description                            | ISM Frequencies |
|--------------|---|--|-----------------|
| PDTIOT-MCS01 | 16CH LoRa, ETH backhaul only                | Wirnet iBTS Compact - 1LOC868-0W868-EU | 863-874.4MHz    |
| PDTIOT-MCS02 | 16CH LoRa, 2G/3G/4G backhaul + ETH backhaul | Wirnet iBTS Compact - 1LOC868-1W868-EU | 863-874.4MHz    |
| PDTIOT-MCS18 | 16CH LoRa, Double 2G/3G/4G backhaul         | Wirnet iBTS Compact 1LOC 1DW-EUEU      | 863-874.4MHz    |
| PDTIOT-MCS12 | 16CH LoRa, 2G/3G/4G backhaul + ETH backhaul | Wirnet iBTS Compact - 1LOC915-1W915-US | 902-928MHz      |
| PDTIOT-MCS19 | 16CH LoRa, 2G/3G/4G backhaul + ETH backhaul | Wirnet iBTS Compact 1LOC923 1W915-US   | 915-928MHz      |
| PDTIOT-MCS10 | 16CH LoRa, 2G/3G/4G backhaul + ETH backhaul | Wirnet iBTS Compact - 1LOC923-1W923-EU | 915-928MHz      |
| PDTIOT-MCS15 | 16CH LoRa, 2G/3G/4G backhaul + ETH backhaul | Wirnet iBTS Compact - 1LOC923-1W923-AS | 915-928MHz      |

### Common accessories for outdoor installation

|          |                             |   |
|----------|-----------------------------|---|
| KLK03524 | Self-amalgamating tape - 3m | Mounting accessories for outdoor installation |
| KLK03540 | Stainless Steel Hose clamp  | Mounting accessories for outdoor installation |

### 868 Accessory Ordering References (Wirnet™ iBTS Compact)

| DC/DC CONVERTER             |  |   |                       |
|-----------------------------|--|---|-----------------------|
| KLK02898                    | Power Supply                             | 40W - DC/DC CONVERTER - 48VDC Input                           |                       |
| PoE INJECTOR                | Designation                              | Description   | Recommendation        |
| KLK03525                    | POE Injector                             | PoE Injector 30 W indoor – 48V DC Input                       |                       |
| KLK03505                    | POE Injector                             | PoE Injector 30 W indoor - AC Input - EU                      |                       |
| KLK03554                    | In addition to KLK03505                  | AC Power supply cable for <b>UK (IEC-320-C13)</b>             |                       |
| KLK03596                    | POE Injector                             | PoE Injector - 30 W Outdoor - AC Input                        |                       |
| EXTERNAL ANTENNA (optional) |  |   |                       |
| ACCIOT-KAN00                | Antenna + 1m cable + support included    | Antenna kit Omni 868 MHz 3 dBi                                |                       |
| ACCIOT-KAN01                | Antenna + 1m cable + support included    | Antenna kit Omni 868 MHz 6 dBi                                |                       |
| ACCIOT-KAN06                | Product Subpart                          | Connectivity kit for antenna diversity (Antenna not included) |                       |
| (Outdoor) CAVITY FILTER     |  |   |                       |
| KLK02523                    | Cavity filter 865-867 MHz                | India   |                       |
| KLK02916                    | CAVITY FILTER 863-873 MHz - OUTDOOR      | EU coexistence high power emitters                            | (former ACCIOT-CAV04) |
| KLK03410_01                 | Cavity filter 865-870 MHz                | 865-870 MHz, EU coexistence LTE800, RGSM                      |                       |
| SURGE PROTECTION            |  |   |                       |
| KLK02817                    | Surge Protection for POE link - Outdoor  | PoE Surge protection - outdoor                                | Recommended           |
| KLK02818                    | Surge Protection for POE link - Indoor   | PoE Surge protection - Indoor                                 | Recommended           |
| KLK02881                    | Surge Protection - DC Link – Indoor      | DC Input  |                       |
| KLK02900                    | Surge Protection for Lora link - Outdoor | RF coaxial Surge protection - outdoor                         | Recommended           |
| ACCWM2-SDE00                | Debug Probe                              | Wirnet iBTS / Wirma Debug Probe                               |                       |

All product specifications are subject to change without notice (V2.7)

**kerlink**  
communication is everything

**Wirnet™ iBTS**  
LoRaWAN® Outdoor Gateway for the Internet of Things

### 915 Accessory Ordering References (Wirnet™ iBTS Compact)

| DC/DC CONVERTER             |  |   |                |
|-----------------------------|--|---|----------------|
| KLK02898                    | Power Supply                             | 40W - DC/DC CONVERTER - 48VDC Input                           |                |
| PoE INJECTOR                |  | Description   | Recommendation |
| KLK03525                    | PoE Injector                             | PoE Injector 30 W indoor – 48V DC Input                       |                |
| KLK03505                    | PoE Injector                             | PoE Injector 30 W indoor - AC Input - EU                      |                |
| KLK03506                    | PoE Injector                             | PoE Injector 30 W indoor - AC Input - US                      |                |
| KLK03596                    | PoE Injector                             | PoE Injector - 30 W Outdoor - AC Input                        |                |
| EXTERNAL ANTENNA (optional) |  |   |                |
| ACCIOT-KAN02                | Antenna + 1m cable + support included    | Antenna kit Omni 915/923 MHz 6 dBi                            |                |
| ACCIOT-KAN03                | Antenna + 1m cable + support included    | Antenna kit Omni 915/923 Mhz 3 dBi                            |                |
| ACCIOT-KAN06                | Product Subpart                          | Connectivity kit for antenna diversity (Antenna not included) |                |
| SURGE PROTECTION            |  |   |                |
| KLK02817                    | Surge Protection for POE link - Outdoor  | PoE Surge protection - outdoor                                |                |
| KLK02818                    | Surge Protection for POE link - Indoor   | PoE Surge protection - Indoor                                 |                |
| KLK02881                    | Surge Protection - DC Link – Indoor      | DC Input  |                |
| KLK02900                    | Surge Protection for Lora link - Outdoor | RF coaxial Surge protection - outdoor                         | Recommended    |
| (Outdoor) CAVITY FILTER     |  |   |                |
| KLK02906                    | Cavity filter 915-920MHz                 | Philippines, Israel, Cuba                                     |                |
| KLK02973                    | Cavity filter 902-928MHz                 | USA, Canada, Mexico   |                |
| DEBUG                       |  |   |                |
| ACCWM2-SDE00                | Debug Probe                              | Wirnet iBTS / Wirma Debug Probe                               |                |

### 923 Accessory Ordering References (Wirnet™ iBTS Compact)

| DC/DC CONVERTER             |  |   |                |
|-----------------------------|--|---|----------------|
| KLK02898                    | Power Supply                             | 40W - DC/DC CONVERTER - 48VDC Input                           |                |
| PoE INJECTOR                |  | Description   | Recommendation |
| KLK03525                    | PoE Injector                             | PoE Injector 30 W indoor – 48V DC Input                       |                |
| KLK03505                    | PoE Injector                             | PoE Injector 30 W indoor - AC Input - EU                      |                |
| KLK03055                    | In addition to KLK03505                  | AC Power supply cable for <b>Japan (IEC-320-C13)</b>          |                |
| KLK03553                    | In addition to KLK03505                  | AC Power supply cable for <b>Australia (IEC-320-C13)</b>      |                |
| KLK03596                    | PoE Injector                             | PoE Injector - 30 W Outdoor - AC Input                        |                |
| EXTERNAL ANTENNA (optional) |  |   |                |
| ACCIOT-KAN02                | Antenna + 1m cable + support included    | Antenna kit Omni 915/923 MHz 6 dBi                            |                |
| ACCIOT-KAN03                | Antenna + 1m cable + support included    | Antenna kit Omni 915/923 Mhz 3 dBi                            |                |
| ACCIOT-KAN06                | Product Subpart                          | Connectivity kit for antenna diversity (Antenna not included) |                |
| SURGE PROTECTION            |  |   |                |
| KLK02817                    | Surge Protection for POE link - Outdoor  | PoE Surge protection - outdoor                                |                |
| KLK02818                    | Surge Protection for POE link - Indoor   | PoE Surge protection - Indoor                                 |                |
| KLK02881                    | Surge Protection - DC Link – Indoor      | DC Input  |                |
| KLK02900                    | Surge Protection for Lora link - Outdoor | RF coaxial Surge protection - outdoor                         | Recommended    |
| (Outdoor) CAVITY FILTER     |  |   |                |
| KLK02522                    | Cavity filter 920-925 MHz                | South Korea, Singapore, HK, Taiwan, Thailand, Cambodia        |                |
| KLK02905                    | Cavity filter 918-923 MHz                | Indonesia Malaysia, Vietnam, Myanmar                          |                |
| KLK02909_01                 | Cavity filter 920-928 MHz                | New-Zealand, Japan, Costa Rica, Venezuela                     |                |
| KLK03306                    | Cavity filter 915-928 MHz                | APAC, LATAM   |                |
| DEBUG                       |  |   |                |
| ACCWM2-SDE00                | Debug Probe                              | Wirnet iBTS / Wirma Debug Probe                               |                |

All product specifications are subject to change without notice (V2.7)

**kerlink**  
communication is everything

**Wirnet™ iBTS**  
LoRaWAN® Outdoor Gateway for the Internet of Things

## Wirnet™ iBTS Full - Ordering references

### Product Ordering References

| Reference    | Designation                    | Description                                 | ISM Frequencies |
|--------------|--------------------------------|---|-----------------|
| PDTIOT-MSS16 | Wirnet iBTS - 1LOC923-1W923-AS | 16CH LoRa, 2G/3G/4G backhaul + ETH backhaul | 915-928MHz      |

### Common accessories for outdoor installation

|          |                             |   |  |
|----------|-----------------------------|---|--|
| KLK03524 | Self-amalgamating tape - 3m | Mounting accessories for outdoor installation |  |
| KLK03540 | Stainless Steel Hose clamp  | Mounting accessories for outdoor installation |  |

### 868 Accessory Ordering References (Wirnet™ iBTS Full)

|                                    |  |   |             |
|------------------------------------|--|---|-------------|
| <b>DC/DC CONVERTER</b>             |  |   |             |
| KLK02882                           | Power Supply                             | 60W - DC/DC CONVERTER 48VDC input                             |             |
| KLK02898                           | Power Supply                             | 40W - DC/DC CONVERTER - 48VDC Input                           | 16 CH only  |
| <b>PoE INJECTOR</b>                |  |   |             |
| KLK03505                           | POE Injector                             | PoE Injector 30 W indoor - AC Input - EU                      | 16 CH only  |
| KLK03550                           | POE Injector                             | PoE Injector - 60 W indoor - AC Input                         |             |
| KLK03554                           | In addition to KLK03505, KLK03550        | AC Power supply cable for <b>UK (IEC-320-C13)</b>             |             |
| <b>EXTERNAL ANTENNA (optional)</b> |  |   |             |
| ACCLOT-KAN00                       | Antenna + 1m cable + support included    | Antenna kit Omni 868 MHz 3 dBi                                |             |
| ACCLOT-KAN01                       | Antenna + 1m cable + support included    | Antenna kit Omni 868 MHz 6 dBi                                |             |
| ACCLOT-KAN05                       | Antenna                                  | Kit WAN 700-2700 MHz 5dBi - 5m - N Male                       |             |
| ACCLOT-KAN06                       | Product Subpart                          | Connectivity kit for antenna diversity (Antenna not included) |             |
| <b>(Outdoor) CAVITY FILTER</b>     |  |   |             |
| KLK02523                           | Cavity filter 865-867 MHz                | India   |             |
| KLK02916                           | Cavity filter 868 MHz                    | 863-873MHz - EU coexistence high power emitters               |             |
| KLK03410_01                        | Cavity filter 865-870 MHz                | 865-870 MHz, EU coexistence LTE800, RGSM                      |             |
| <b>SURGE PROTECTION</b>            |  |   |             |
| KLK02817                           | Surge Protection for POE link - Outdoor  | PoE Surge protection - Outdoor                                | Recommended |
| KLK02818                           | Surge Protection for POE link - Indoor   | PoE Surge protection - Indoor                                 | Recommended |
| KLK02819                           | RF Surge Protection for GSM and GPS Link | RF Surge protection - LoRa                                    | Recommended |
| KLK02881                           | Surge Protection - DC Link - Indoor      | DC Input  |             |
| KLK02900                           | Surge Protection for Lora link - Outdoor | RF coaxial Surge protection - Outdoor                         | Recommended |
| <b>DEBUG</b>                       |  |   |             |
| ACCWM2-SDE00                       | Debug Probe                              | Wirnet iBTS / Wirma Debug Probe                               |             |

All product specifications are subject to change without notice (V2.7)

**kerlink**  
communication is everything

**Wirnet™ iBTS**  
LoRaWAN® Outdoor Gateway for the Internet of Things

### 915 Accessory Ordering References (Wirnet™ iBTS Full)

| DC/DC CONVERTER             |   |   |             |
|-----------------------------|---|---|-------------|
| KLK02898                    | Power Supply                              | 40W - DC/DC CONVERTER - 48VDC Input                           | 16 CH only  |
| KLK02882                    | Power Supply                              | 60W - DC/DC CONVERTER 48VDC input                             |             |
| PoE INJECTOR                |   |   |             |
| KLK03525                    | POE Injector                              | PoE Injector 30 W indoor – 48V DC Input                       | 16 CH only  |
| KLK03505                    | POE Injector                              | PoE Injector 30 W indoor - AC Input - EU                      | 16 CH only  |
| KLK03506                    | POE Injector                              | PoE Injector 30 W indoor - AC Input - US                      |             |
| KLK03550                    | POE Injector                              | PoE Injector - 60 W indoor - AC Input                         |             |
| EXTERNAL ANTENNA (optional) |   |   |             |
| ACCIOT-KAN02                | Antenna + 1m cable + support included     | Antenna kit Omni 915/923 MHz 6 dBi                            |             |
| ACCIOT-KAN03                | Antenna + 1m cable + support included     | Antenna kit Omni 915/923 MHz 3 dBi                            |             |
| ACCIOT-KAN05                | Antenna WAN + 5m cable + support included | Kit WAN 700-2700 MHz 5dBi - 5m - N Male                       |             |
| ACCIOT-KAN06                | Product Subpart                           | Connectivity kit for antenna diversity (Antenna not included) |             |
| (Outdoor) CAVITY FILTER     |   |   |             |
| KLK02973                    | Cavity filter 902-928MHz                  | USA, Canada, Mexico   |             |
| KLK02906                    | Cavity filter 915-920 MHz                 | Philippines, Israel, Cuba                                     |             |
| SURGE PROTECTION            |   |   |             |
| KLK02817                    | Surge Protection for POE link - Outdoor   | PoE Surge protection - Outdoor                                |             |
| KLK02818                    | Surge Protection for POE link - Indoor    | PoE Surge protection - Indoor                                 |             |
| KLK02819                    | RF Surge Protection for GSM and GPS Link  | RF Surge protection - LoRa                                    | Recommended |
| KLK02881                    | Surge Protection - DC Link – Indoor       | DC Input  |             |
| KLK02900                    | Surge Protection for Lora link - Outdoor  | RF coaxial Surge protection - Outdoor                         | Recommended |
| DEBUG                       |   |   |             |
| ACCWM2-SDE00                | Debug Probe                               | Wirnet iBTS / Wirma Debug Probe                               |             |

### 923 Accessory Ordering References (Wirnet™ iBTS Full)

| DC/DC CONVERTER             |   |   |             |
|-----------------------------|---|---|-------------|
| KLK02898                    | Power Supply                              | 40W - DC/DC CONVERTER - 48VDC Input                           | 16 CH only  |
| KLK02882                    | Power Supply                              | 60W - DC/DC CONVERTER 48VDC input                             |             |
| PoE INJECTOR                |   |   |             |
| KLK03525                    | POE Injector                              | PoE Injector 30 W indoor – 48V DC Input                       | 16 CH only  |
| KLK03505                    | POE Injector                              | PoE Injector 30 W indoor - AC Input - EU                      | 16 CH only  |
| KLK03055                    | In addition to KLK03505                   | AC Power supply cable for <b>Japan (IEC-320-C13)</b>          |             |
| KLK03550                    | POE Injector                              | PoE Injector - 60 W indoor - AC Input                         |             |
| KLK03553                    | In addition to KLK03505                   | AC Power supply cable for <b>Australia (IEC-320-C13)</b>      |             |
| EXTERNAL ANTENNA (optional) |   |   |             |
| ACCIOT-KAN02                | Antenna + 1m cable + support included     | Antenna kit Omni 915/923 MHz 6 dBi                            |             |
| ACCIOT-KAN03                | Antenna + 1m cable + support included     | Antenna kit Omni 915/923 MHz 3 dBi                            |             |
| ACCIOT-KAN05                | Antenna WAN + 5m cable + support included | Kit WAN 700-2700 MHz 5dBi - 5m - N Male                       |             |
| ACCIOT-KAN06                | Product Subpart                           | Connectivity kit for antenna diversity (Antenna not included) |             |
| (Outdoor) CAVITY FILTER     |   |   |             |
| KLK02522                    | Cavity filter 920-925 MHz                 | South Korea, Singapore, HK, Taiwan, Thailand, Cambodia        |             |
| KLK02905                    | Cavity filter 918-923 MHz                 | Indonesia Malaysia, Vietnam, Myanmar                          |             |
| KLK02909_01                 | Cavity filter 920-928 MHz                 | New-Zealand, Japan, Costa Rica, Venezuela                     |             |
| KLK03306                    | Cavity filter 915-928 MHz                 | APAC, LATAM   |             |
| SURGE PROTECTION            |   |   |             |
| KLK02817                    | Surge Protection for POE link - Outdoor   | PoE Surge protection - Outdoor                                |             |
| KLK02818                    | Surge Protection for POE link - Indoor    | PoE Surge protection - Indoor                                 |             |
| KLK02819                    | RF Surge Protection for GSM and GPS Link  | RF Surge protection - LoRa                                    | Recommended |
| KLK02881                    | Surge Protection - DC Link – Indoor       | DC Input  |             |
| KLK02900                    | Surge Protection for Lora link - Outdoor  | RF coaxial Surge protection - Outdoor                         | Recommended |
| DEBUG                       |   |   |             |
| ACCWM2-SDE00                | Debug Probe                               | Wirnet iBTS / Wirma Debug Probe                               |             |

All product specifications are subject to change without notice (V2.7)